

GE SKU	GE DS SKU	TU SKU	TU DS SKU	Product Description
93094461	93094462	93094467	93094468	LED Start MR16 7W(50) 827 35° 1/8
93094463	93094464	93094469	93094470	LED Start MR16 7W(50) 830 35° 1/8
93094465	93094466	93094471	93094472	LED Start MR16 7W(50) 840 35° 1/8



	Brand	Model	Dimmable ET	One lamp (198V-->254V)	Two lamp	Three lamp
24	OSRAM	ET-P60	Y	CM<90% (87.6%)	N/A	N/A
25		ET-Z60	N	PASS	N/A	N/A
26		ET-PARRORT 70W	Y	PASS	N/A	N/A
27		ECO-ET 60	Y	PASS	N/A	N/A
28		ECO-ET 105W	Y	FLICKER	PASS	N/A
29		HTM 105W	Y	PASS	N/A	N/A
30		HTM 70W	Y	PASS	N/A	N/A
31		HTI DALI 150W	Y	Damaged	N/A	N/A
32		Redback 60W	Y	Damaged	N/A	N/A
33		ECP	ECP Halogen Transformer	Y	PASS	N/A
34	Philips	ET-E 50A26	N	FLICKER	N/A	N/A
35		ET-E 60	J	FLICKER	PASS	N/A
36		ET-S 60	Y	FLICKER	PASS	N/A
37		Certaline 60W	Y	FLICKER	N/A	N/A
38		Primaline 105W	Y	PASS	N/A	N/A
39		Primaline 70W	Y	CM<90% (88%)	N/A	N/A
40		0	Y	Damaged	N/A	N/A
41	ANDAWO	MR-128	N	Not found	N/A	N/A
42	Merlox	ET50/12	N	Damaged	N/A	N/A
43	NVC 雷士	ET60E	N	FLICKER	N/A	N/A
44		ET50S	N	PASS	N/A	N/A
45	GE	SET60LV	N	PASS	N/A	N/A
46		SET60LTD	N	PASS	N/A	N/A
47		EEP60LS	Y	PASS	N/A	N/A
48	JCC	JC4030	N	PASS	N/A	N/A
49	Tridonic	VIPER 22176074 105W	Y	Damaged	N/A	N/A
50		VIPER 22176072 60W	Y	PASS	N/A	N/A
51		VIPER 22176070 60W	Y	PASS	N/A	N/A
52		Possum	Y	PASS	N/A	N/A
53		Speedy	Y	PASS	N/A	N/A
54		TE-0060	N	N/A	N/A	N/A
55		TMDC 50(Magnetic)	Y	PASS	N/A	N/A
56	Aurora	S60	Y	PASS	N/A	N/A
57	AcTEC	Mini60	Y	PASS	N/A	N/A
58	Lighttech	LET60/230V	Y	PASS	N/A	N/A
59		LET105/240V 97431	Y	PASS	N/A	N/A
60		105/240V With Dimmer 97	Y	PASS	N/A	N/A
61		LET75/Lite Beetle 97418	Y	PASS	N/A	N/A
62		LET75/240V 97417	Y	PASS	N/A	N/A
63		12VDC 12W LED driver	Y	PASS	N/A	N/A
64		12VDC 25W LED driver	Y	PASS	N/A	N/A
65	12VDC 60W LED driver	Y	PASS	N/A	N/A	
66	Maxel	70	Y	CM<90%	N/A	N/A
67		105	Y	Can't start	PASS	N/A
68		210	Y	Can't start	CM<90%	N/A
69	Nobile	EN-60D	Y	PASS	N/A	N/A
70		EN-80D	Y	FLICKER	N/A	N/A
71	TCI	MW70	N	PASS	N/A	N/A
72		Round 60	Y	PASS	N/A	N/A
73	HEP	TB60M 10-60W Dimmable	Y	PASS	N/A	N/A
74	Vossloh Schawabe	EST60/12.635	N	CM<90%	N/A	N/A
75		EST60/12.301	N	FLICKER	N/A	N/A
76		ST 60/12.633 non-dimmab	N	N/A	N/A	N/A
77	LCI	ET3-60	Y	PASS	N/A	N/A
78	Stratus	LVT4502 105W	Y	N/A	N/A	N/A
79	Newlec	NLLVLC60DL 20--60W	Y	PASS	N/A	N/A
80	ROBUS	LEB60D 20--60W	Y	PASS	N/A	N/A
81		RAPS-70D 20--70W	Y	Can't start	Pass	N/A
82	Daiko	DP-36282E./DP-36283E	Y	N/A	N/A	N/A
83	Koizumi	AEE690156/ AEE690157	Y	N/A	N/A	N/A
84	Panasonic	HNK00844	Y	N/A	N/A	N/A
85	Toshiba	DTF-36	N	N/A	N/A	N/A
86	Lighttech	LET 120/230	Y	PASS	N/A	N/A
87	Vossloh Schawabe	EST60/12.633	N	N/A	N/A	N/A
88	MW	APV-12-12	N	PASS	N/A	N/A
89	GE	ET-15/220-240V	N	PASS	N/A	N/A
90	OSRAM	ET-C 70/220-240	N	PASS	N/A	N/A

GE SKU	GE DS SKU	TU SKU	TU DS SKU	Product Description
93095381	93095382	93094225	93094456	LED Start MR16 5W(35) 827 35° 1/8
93095383	93095384	93094457	93094458	LED Start MR16 5W(35) 830 35° 1/8
93095385	93095386	93094459	93094460	LED Start MR16 5W(35) 840 35° 1/8



	Brand	Model	Dimmable ET	One lamp (198V-->254V)	Two lamp	Three lamp
16	EZ lighting	LED converter 10SL	N	N/A	N/A	N/A
17		SI-H2501SL	N	N/A	N/A	N/A
18		EL-Time	OS-HG50	N	N/A	N/A
19	Day-Time	AL-2250HB	N	N/A	N/A	N/A
20	DAWOO Bank	TL-H50	Y	PASS	N/A	N/A
21		Day-dream	N	N/A	N/A	N/A
22		Doo Young(DYH-50)	N	N/A	N/A	N/A
23		Halogen	N	N/A	N/A	N/A
24	OSRAM	ET-P60	Y	PASS	N/A	N/A
25		ET-Z60	N	>228v FLICKER	N/A	N/A
26		ET-PARRORT 70W	Y	>232v FLICKER	N/A	N/A
27		ECO-ET 60	Y	PASS	N/A	N/A
28		ECO-ET 105W	Y	PASS	PASS	N/A
29		HTM 150W	Y	PASS	PASS	N/A
30		HTM 70W	Y	PASS	N/A	N/A
31		HTI DALI 150W	Y	Damaged	N/A	N/A
32		Redback 60W	Y	Damaged	N/A	N/A
33	ECP	CP Halogen Transform	Y	Not find	N/A	N/A
34	Philips	ET-E 50A26	N	>221v FLICKER	N/A	N/A
35		ET-E 60	J	PASS	PASS	N/A
36		ET-S 60	Y	PASS	PASS	N/A
37		Certaline 60W	Y	PASS	PASS	N/A
38		Primaline 105W	Y	PASS	PASS	N/A
39		Primaline 70W	Y	PASS	PASS	N/A
40		0	Y	Damaged	N/A	N/A
41	ANDAWO	MR-128	N	PASS	N/A	N/A
42	Merlox	ET50/12	N	Damaged	N/A	N/A
43	NVC 雷士	ET60E	N	PASS	N/A	N/A
44		ETS0S	N	PASS	N/A	N/A
45	GE	SET60LV	N	PASS	N/A	N/A
46		SET60LTD	N	PASS	N/A	N/A
47		EEP60LS	Y	PASS	N/A	N/A
48	JCC	JC4030	N	PASS	N/A	N/A
49	Tridonic	VIPER 22176074 105W	Y	Damaged	N/A	N/A
50		VIPER 22176072 60W	Y	Slight flicker@220-225V	N/A	N/A
51		VIPER 22176070 60W	Y	PASS	N/A	N/A
52		Possum	Y	Flicker@220V	N/A	N/A
53		Speedy	Y	PASS	N/A	N/A
54			TE-0060	N	N/A	N/A
55		TMDC 50(Magnetic)	Y	PASS	N/A	N/A
56	Aurora	S60	Y	PASS	N/A	N/A
57	AcTEC	Mini60	Y	PASS	PASS	N/A
58	Lightech	LET60/230V	Y	PASS	N/A	N/A
59		LET105/240V 97431	Y	PASS	N/A	N/A
60		105/240V With Dimmer	Y	PASS	N/A	N/A
61		LET75/Lite Beetle 97418	Y	can't light up	N/A	N/A
62		LET75/240V 97417	Y	PASS	N/A	N/A
63		12VDC 12W LED driver	Y	PASS	N/A	N/A
64	12VDC 25W LED driver	Y	PASS	N/A	N/A	
65	12VDC 60W LED driver	Y	PASS	N/A	N/A	
66	Maxel	70	Y	PASS	N/A	N/A
67		105	Y	Flicker@220-225V	N/A	N/A
68		210	Y	Slight flicker, CM<90%	PASS	N/A
69	Nobile	EN-60D	Y	PASS	N/A	N/A
70		EN-80D	Y	PASS	N/A	N/A
71	TCI	MW70	N	PASS	N/A	N/A
72		Round 60	Y	PASS	N/A	N/A
73	HEP	960M 10-60W Dimmab	Y	PASS	N/A	N/A
74	Vossloh Schawabe	EST60/12.635	N	PASS	N/A	N/A
75		EST60/12.301	N	PASS	N/A	N/A
76		60/12.633 non-dimma	N	N/A	N/A	N/A
77	LCI	ET3-60	Y	PASS	N/A	N/A
78	Stratus	LVT4502 105W	Y	N/A	N/A	N/A
79	Newlec	LLLVLCG0DL 20-60W	Y	PASS	N/A	N/A
80		LEB60D 20-60W	Y	PASS	Pass	N/A
81	ROBUS	RAPS-70D 20-70W	Y	Slight flicker@<222V	Pass	N/A
82	Daiko	DP-36282E./DP-36283E	Y	N/A	N/A	N/A
83	Koizumi	AEE690156/ AEE690157	Y	N/A	N/A	N/A
84	Panasonic	HNK00844	Y	N/A	N/A	N/A
85	Toshiba	DTF-36	N	N/A	N/A	N/A
86	Lightech	LET 120/230	Y	PASS	N/A	N/A
87	Vossloh Schawabe	EST60/12.633	N	N/A	N/A	N/A
88	MW	APV-12-12	N	PASS	N/A	N/A
89	GE	ET-15/220-240V	N	PASS	N/A	N/A
90	OSRAM	ET-C 70/220-240	N	PASS	N/A	N/A

Standard SKU	Description	Direct Shipment SKU	Description
93061072	LED Specialty PAR56 16W(300) 765 90° BX	93084485	LED Specialty PAR56 16W(300)765 90° BXDS



93077313	LED Specialty PAR56 16W(300) 765 90° TU	93103574	LED Specialty PAR56 16W(300) 765 90°TUDS
93104930	LED Specialty PAR56 16W(300) 730 90° TU	93104941	LED Specialty PAR56 16W(300) 730 90°TUDS



These 12V PAR56 lamps are compatible with all electromagnetic transformers where the transformer output is 12V and at least 2A.
Do NOT use with electronic transformers!